


BRD-500 series

Low Voltage SmartDIM Occupancy Sensor



OVERVIEW

The BRD-500 series member of the TRANS family is a two-way IR remote programmable low voltage occupancy sensor with an isolated dry contact for power pack switching and 0-10V output for dimming controls. The sensor is capable of providing fully programmable multi-level high/low dim or SmartDIM control in various modes to achieve top-notch energy efficient lighting control. **SmartDIM** is a state-of-the-art automatic dimming control technology developed by IR-TEC, which is capable of maintaining the overall ambient light level within the preset range through a smooth, flawless continuous dimming control to the connected lighting.

The sensor will turn on the light connected via an IR-TEC power pack to the high dim or SmartDIM level as programmed when it detects the presence of an occupant or vehicle, and automatically dim the light down to the low level or shut off as programmed after the area is vacated for a period of time. An exclusive two-way handheld remote programmer allows you to configure sensor setting, or download the existing settings of the installed sensor from the floor.

Like all PIR sensors in the TRANS family, the BRD-500 series is also available with various mounting options and interchangeable lenses. This provides a second-to-none design and complete installation flexibility. The sensor is designed to operate in the coldest of environments, down to -40°C/°F.

APPLICABLE REMOTE (order separately)

| Model | Description | Remarks |
|---------|-------------------------|---------------------------------------|
| SRP-280 | TRANS Remote Programmer | Full functionality |
| URP-100 | User Remote | Manual ON/OFF/DIM TIME/LUX setting |

FEATURES

- Omni-directional digital pyroelectric infrared sensor
- Digital data control ambient light sensor built-in
- 2-way IR remote programmable sensor setting
- Isolated dry contact and 0-10V control outputs
- SmartDIM or multi-level high/low dim control
- Remote programmable SmartDIM level setting
- Occupancy/vacancy/daylight sensing controls
- Up to 10 m of remote programmable range
- Beeping or light flashing acknowledgement
- Available with a variety of mounting options
- Available with interchangeable lens options

APPLICATION

- ☒ 0-10V Continuous Dimming Control
- ☒ 0-10V Multi-level Dimming Control

The BRD-500 series sensor can be used to provide occupancy/vacancy sensing based, multi-mode, continuous dimming control by sensing the presence and movements of the occupant and the daylight available in the space. Specific control mode and sensor setting can be configured via the SRP-280 remote sensor programmer (optional). Within the maximum load allowed by the power pack, one BRD-500 sensor can control up to 50 dimmable ballasts/drivers with sinking current less than 0.5mA each. Basic wiring diagram is included at next page for reference. Consult with an IR-TEC team member if a more complex control is required.

BRD-500 series

Low Voltage SmartDIM Occupancy Sensor

SmartDIM

SmartDIM is an exclusive continuous dimming control algorithm developed by IR-TEC to provide a smooth and flawless automatic dimming performance. The output of the controlled lighting will be constantly adjusted to maintain the overall ambient light level within the pre-programmed range by sensing the daylight available in the space.

CONTROL MODES

The BRD-500 series can be programmed by SRP-280 to control the lighting in one of the following modes with various conditions as set. For more details of specific control mode, please visit www.irtec.com or contact an IR-TEC team member directly.

| Mode | Day ¹ | Night ² | Remarks |
|--------|--------------------------|----------------------------|---|
| ON/OFF | Vac: OFF Occ: ON/OFF* | Vac: OFF Occ: ON | For non-dimmable lighting *ALS enabled |
| OSO | Vac: LD Occ: SD/HD | Vac: LD Occ: SD/HD | LD: Low Dim, HD: High Dim SD: SmartDIM |
| OSLA | Vac: OFF Occ: SD/OFF | Vac: LD Occ: SD/HD | |
| OSLATO | Vac: OFF Occ: SD/OFF | Vac: LD*-OFF Occ: SD/HD | *Low Dim during Time Off delay |
| OFF | Vac: OFF Occ: OFF | Vac: OFF Occ: OFF | Light stays off |

ON/OFF : ON-OFF Switching

OSO : Occupancy Sensing Only

OSLA : Occupancy Sensing at Low Ambient

OSLATO : Occupancy Sensing at Low Ambient with Time-Off

OFF : Light OFF all the time

Vac : Vacant Occ : Occupied

¹ While ambient light level is higher than the threshold.

² While ambient light level is lower than the threshold.

MOUNTING OPTIONS

The BRD-500xx series can be mounted into the ceiling or integrated with an OEM lighting fixture. The mounting options are available by combining a specific mounting bracket (if applicable) from the table below. The bracket will be shipped with the sensor when ordered with the respective code.

| Code | Mounting Option | Mounting Bracket |
|------|--------------------------|------------------|
| F | Fixture Integrated | --- |
| W | IP-66 Fixture Integrated | --- |
| E | Fixture External | EMB-500 |
| P | IP-66 Fixture External | PMB-500 |
| S | Ceiling Surface | SMB-500 |
| C | Junction Box | CMB-500 |
| R | Ceiling Recess | RMB-500 |


LENS OPTIONS

The BRD-500xx series is available with following lens options which provide different coverage at different mounting height (H). When adding the lens code, the lens is then automatically shipped with the sensor.

| Lens | Shape | Mounting Height | Coverage |
|------|------------|-----------------|---------------------|
| A | Standard | Cone | 8~15 ft. 2.4~4.5m |
| B | Extra wide | Cone | 8~10 ft. 2.4~3.0m |
| C | High bay | Cone | 15~30 ft. 4.5~9.0m |
| D | Standard | Round | 8~20 ft. 2.4~6.0m |
| E | Extra wide | Dome | 8~20 ft. 2.4~6.0m |
| F | Aisle way | Arch | 8~40 ft. 2.4~12.0m |
| H | High bay | Dome | 30~50 ft. 9.0~15.0m |
| L | Long aisle | Arch | 8~10 ft. 2.4~3.0m |

WIRING DIAGRAM

SmartDIM control with power pack



NOTE: Each IR-TEC PPU-300/301 power pack can supply power for up to 6 BRD-500 sensors. When more sensors are connected, multiple power packs may be required.

SPECIFICATIONS

| | |
|------------------|---|
| Power voltage | 12-24 VDC |
| Current Drain | 11/23 mA @ 24 VDC, vacant/occupied |
| Infrared sensor | Omni-directional pyroelectric |
| Photo sensor | Digital ambient light sensor |
| Sensor output | Isolated dry contact, 48 VDC, 1A max. |
| Dim control | 0-10V, $\pm 5\%$, max. 25 mA sinking current |
| Detectable speed | 0.3 ~ 3 m/sec. (1~10 ft./sec.) |
| Mounting height | Subject to the lens type applied |
| Detection range | Subject to the lens applied and height |
| Remote range | 10 m (33 ft) indoor |
| Op. humidity | Max. 95% RH |
| Op. temperature | -40°C~55°C (-40°F~131°F) |
| Dimensions | Ø60 x H37mm (Ø2.36"x H1.45") |