

ON-MRD-510 series

SmartDALI OS-NET Sensor

INSTALLATION INSTRUCTIONS





w/Lens A/B/C

w/Lens G

w/Lens F

*More lens options are available for this sensor. Please refer to the Lens Datasheet for more details.

WARNING & CAUTION

- Risk of Electric Shock Disconnect power supply before servicing.
- Do NOT touch the square window of infrared sensor under the lens assembly
- Use AWG 16-20 solid conductor wires Strip length 8-9 mm / 0.31-0.35 in.
- Open Type Photoelectric Switches.
- Cycling the power to the sensors will cause failure over time.

AVERTISSEMENT & PRUDENCE

- Risque de choc électrique Débranchez l'alimentation avant l'entretien.
- Ne PAS toucher la fenêtre carrée de capteur infrarouge sous l'ensemble de l'obiectif
- Utilisez AWG 16-20 fils conducteurs solidesLongueur de la bande de 8-9 mm / de 0.31 à 0.35 en.
- Ouvrir Type commutateurs optoélectroniques.



OVERVIEW

The ON-MRD-510 series is an OS-NET Sensor (ONS) packed with multiple sensing control functionalities including occupancy/vacancy sensing, daylight harvesting, bi-level StepDIM or continuous SmartDIM, and wireless mesh networking capability for top-notch intelligent lighting control.

Being a member of Omni ONS, this sensor can be flexibly integrated with an OEM luminaire, or mounted on the ceiling in a variety of options. Changeable lens options allow the sensor to be mounted at various heights with different detection patterns for all applications. All functionalities can be easily and intuitively configured by a 2-way remote programmer from the floor. With ON-MRD-510, you can effortlessly achieve energy efficient, code-compliant smart lighting control through a wireless sensor mesh network effortlessly deployed while installing the OS-NET enabled lighting.

SPECIFICATIONS

Power supply	230-240VAC or DALI bus power
Infrared sensor	Digital quad-element pyroelectric sensor
DALI bus power	60 mA max. (can be disabled)
Control protocol	DALI Broadcast
Wireless protocol	Modified Zigbee Light Link (ZLL)
Radio frequency	2405~2480MHz
Number of Channel	16ch
Radio range	15/90 m @indoor/outdoor, open space
Radio Power Output	6.98dBm
Detectable speed	0.15 ~ 3 m/sec. (0.5~10 ft./sec.)
Mounting height	Subject to the lens applied
Detection range	As per lens applied and mounting height
Remote range	Typ. 10 m (33 ft), indoor with no backlight
Op. humidity	Max. 95% RH
Op. temperature	-40°C~70°C (-40°F~158°F)
Dimensions	Ø60 x H37mm (Ø2.36"x H1.45")

APPLICATION NOTES

- The sensor is more sensitive to the movements "crossing" the detection zones than "toward" or "away" the sensor unit. To obtain better sensitivity, avoid placing the sensor in line with occupant path.
- 2. The closer the movement is to the sensor, the more sensitive the sensor is. The higher the sensor is installed, the larger movement is required to be detected.
- 3. Ensure to place the sensor at least at 1.5m (5 ft.) away from air supply ducts as rapid air flow may cause false activations.
- The sensor cannot "see" the movements behind obstacles, such as tall furniture, shelf, glass or partitions. Avoid placing the sensor where obstructions may block the sensor's line of sight.
- 5. The partition of workstation could block the sensor view to occupant movements, it is best to place the sensor over the intersection of workstation. For large open office, place multiple sensors so that there is overlap coverage with each adjacent sensor.
- 6. To obtain optimal wireless communication range, avoid enveloping the sensor with a metallic enclosure.



MOUNTING

This device can be integrated with a luminaire or mounted on the ceiling in various formats via specific mounting bracket. Please refer to the mounting instruction sheet separately attached for more details about mounting options available.

WIRING DIAGRAM

Powered by line voltage



Powered by DALI bus



OPERATION

The ON-MRD-510 employs a digital PIR sensor together with an ALS to detect occupancy status and ambient light level. The sensor not only controls the connected lighting as programmed when it detects the presence of an occupant/vehicle, but also broadcasts an OCC signal to other devices of the group to activate the respective controls. Each sensor can be assigned to be member of maximum 4 groups for coordinated control.



SETTING

All sensor settings can be configured, in individual or group basis, by an OS-NET Remote Programmer SRP-281. Following table highlights the setting items and options available with ON-MRD-510. For detailed setting operation, please refer to the OS-NET Programming Guide available for download from <u>www.irtec.com</u>.



Settings	Description	Options	Default
INDIV-SET	To setup an individual device		
GROUP-SET	To setup all devices of the group with same settings		
CONTROL	Control schemes available for OS-NET sensor.	ON/OFF, OSO, OSLA, OSLATO, DSVM, DSC, VSC, OSB, OFF	OSLATO
AMBIENT LUX	Thresholds of ambient light level for OS-NET sensor to execute the control.	10/20/40/60/80/200/400/600/1000/2000 LUX DISABLED/CURRENT	DISABLED
DELAY	Delay time that sensor will turn off or fade down the light.	30 sec./1/3/5/10/15/20/30/60 min.	10 min.
TIME OFF	Delay time that sensor will keep the light at low dim level after the OFF delay time elapsed.	10/30 sec./3/5/10/15/20/30/45/60 min.	10 min.
HIGH DIM	High dim is the output level set to control the light during occupancy, or when ambient light is lower than the threshold if daylight sensing scheme is selected.	50/55/60/65/70/80/90/100%/SmartDIM	100%
DALI Power	Enable/disable the sensor to provide DALI bus power. NOTE: If total DALI bus power will exceed 250mA after adding the sensor powered by line voltage, please "DISABLE" the DALI POWER.	ENABLED/DISABLED	ENABLED
LOW DIM/ SmartDIM	Low dim is the output level set to dim the light when space is vacant for bi-level control. Low dim setting will become SmartDIM bar if SmartDIM control is selected.	0/5/10/15/20/25/30/40%	30%
RAMP UP	Speed of lighting output increase.	INSTANT/SOFT/SLOW	INSTANT
FADE DOWN	Speed of lighting output decrease.	INSTANT/SOFT/SLOW	SOFT
LED INDICATOR	Enable or disable the LED indicator of the sensor.	ENABLED/DISABLED	ENABLED
VM-ТВ	Time duration BEFORE Virtual Midnight. Only available if DSVM is selected.	0.5/1/1.5/2/2.5/3/3.5/4/4.5/5/5.5/6 hour	2.5 hours
VM-TA	Time duration AFTER Virtual Midnight. Only available if DSVM is selected.	0.5/1/1.5/2/2.5/3/3.5/4/4.5/5/5.5/6 hour	4 hours
SENSITIVITY	Sensitivity of occupancy sensor. To disable the occupancy sensing capability, select OFF.	HIGH/NORMAL/LOW/OFF	HIGH

SETTING ACKNOWLEDGEMENT

INDICATION	ACKNOWLEDGEMENT	REMARKS
Device LED fast blinking in GREEN and BLUE.	The device is scanning and linking to the network.	The fast blinking (on-off per 0.2 second) only appears during network linking.
Device LED blinks twice every 2-second in GREEN or BLUE.	The sensor detects occupant's motion.	GREEN means the device is network linked. BLUE means the device is unlinked.
Device LED blinks twice every 2-second for 5 minutes, and then 15-second after power applied.	The device is set with daylight sensing control. (DSVM or DSC)	GREEN means the device is network linked. BLUE means the device is unlinked.
Device short beeps twice.	Receiving a single setting or control command.	
Device beeps one long and two short. The connected lights flash twice.	1. Multiple setting data UPLOAD successful. 2. GROUP LINK successful.	
The connected lights flash twice.	 Factory default setting resumed. SmartDIM setting completed. 	

CONTROL MODE

The ON-MRD-510 series can be programmed to control the connected lighting in one of the modes as below.

Scheme	Description
ON/OFF	This is a typical occupancy sensing control scheme.
	Lighting will be inhibited when the ambient light level is higher than the set threshold, regardless of occupancy or vacancy. When
	the ambient light level is lower than the set threshold, the controlled light will be automatically turned on once the sensor detects the
	presence of occupant, and turned off after the delay time elapsed.
060	NOTE: This is an operation of the second sec
050	I mis is an occupancy sensing control scheme can be applied in areas that require 24-hour lighting, when space is vacant, the lights
	Will be maintained at Low Diminevel, whenevel space is occupied, lighting output will be increased to high Diminevel of continuously regulated to maintained at Low Diminevel space is occupied, lighting output will be increased to high Diminevel of continuously
	NOTE: Do NOT use this scheme to control non-dimmable lighting
	This is an occurancy sensing control scheme can be applied in spaces that require automatic lighting when the ambient light level is
OULA	lower than the set threshold.
	Lighting will be inhibited if the ambient light level is higher than the set threshold, regardless of occupancy or vacancy. When the
	ambient light level is lower than the set threshold, the sensor will automatically control the light at Low Dim level. When sensor detects
	the presence of an occupant, lighting output will be increased to the High Dim level or continuously regulated within the pre-set range
	by SmartDIM control. After the delay time elapsed, lighting output will be reduced to Low Dim level or shut off if the ambient light is
	higher than the set threshold.
	NOTE: Do NOT use this scheme to control non-dimmable lighting.
OSLATO	This is an occupancy sensing control scheme can be applied in spaces that require maintaining Low Dim lighting for a period of time
	before shutting off.
	Lighting will be innibited if the ambient light level is higher than the set threshold, regardless of occupancy or vacancy. When the
	lambient ignit level is lower than the set threshold, and any sensor detects the presence of occupant, lighting output will be increased.
	Time elansed lighting output will be reduced to Low Dim level for a period of TIME OFE delay before shut off
	NOTE: This scheme requires dimmable lighting to enabled imming control. If lighting is non-dimmable , there will be no dim control
	and the delay time will be extended with the TIME OFF (TO) delay.
DSVM	This is a daylight sensing control scheme can be applied in spaces that require automatically dimming the lighting output to a low
	level between a certain time before and after virtual midnight.
	Lighting will be inhibited if the ambient light level is higher than the set threshold. When the ambient light level is lower than the set
	threshold, the sensor will turn the light to High Dim level or continuously regulate the output to maintain overall lighting level within the
	pre-set range by SmartDIM control. Lighting output will be reduced to Low Dim level from a certain time before virtual midnight to a
	Certain time after.
	NOTE: This scheme requires dimmable lighting to enable dimming control. If lighting is non-dimmable , all lights will remain on under such as the scheder of the scheder.
000	Whenever ambient light level is lower than the set threshold.
DSC	I has is a daying transmit control scheme can be applied in spaces that require automatic lighting whenever the ambient light is lower than the set through a day and the set
	The service automatically turn on the light to High Dim level or continuously regulate the output to maintain overall lighting level
	within the pre-set range by SmartDIM control when the ambient light level is lower than the set threshold and automatically turn off th
	light when the ambient light level is higher than the set threshold.
	NOTE: This scheme requires dimmable lighting to enable dimming control. If lighting is non-dimmable, all lights will remain on
	whenever ambient light level is lower than the threshold.
VSC	This is a vacancy sensing control scheme can be applied in spaces that require users to manually turn on the light, and have the
	sensor turn off the light automatically.
	The occupant would have to press the OS-NET Button to turn on the lighting group assigned. The sensor will control the lights at High
	Dim level or continuously regulate the output to maintain overall lighting level within the pre-set range by SmartDIM control. The sense
	Will control the connected lighting as per USLALU scheme.
	and the delay time will be extended with the TIME OFF (TO) delay
OSB	This is an advanced occupancy sensing control scheme can be applied in open offices to provide background light level before the
	area of entire lighting group is vacant.
	Lighting will be inhibited if the ambient light level is higher than the set threshold, regardless of occupancy or vacancy. When the
	ambient light level is lower than the set threshold and the first occupant is detected by a grouped sensor, the output of sensor
	connected light will be increased to High Dim level or continuously regulated within the pre-set range by SmartDIM control during
	occupancy, and the unoccupied areas of entire lighting group will brighten up to Low Dim level as background light. The entire lighting
	group turns off after the last person leaves and delay time elapsed.
055	NULE: Do NUL use this scheme to control non-dimmable lighting.
UFF	I his is a manual control scheme can be used when you need the light to be off for a certain period of time.
	Unce this scheme is set, all US-INET controlled lighting will remain off until another scheme is selected.